How to configure a SIP account on a Fanvil IP Phone

Remark: All Phone set configuration process almost the same

- 1. Power up the phone set (PoE or External power adapter).
- 2. Enter to menu, status then note the IP address provided by DHCP server.
- 3. Enter the desk phone IP address on web browser.
- 4. User: admin, password: admin

User:	admin
Password:	•••••
Language:	English 🔻
	Logon

5. Click "Line" Tab.

	SIP Dial Peer	Dial Plan Ba	sic Settings	
> System				
> Network	Line SIP 1 v Basic Settings >>			
> Line	Line Status Username	Registered 1000	SIP Proxy Server Address SIP Proxy Server Port	192.168.9.144 5060
> Phone settings	Display name Authentication Name	1000 1000	Outbound proxy add. Outbound proxy port	
> Phonebook	Authentication Password Activate	••••• ✓	Realm	
> Call logs	Codecs Settings >> Advanced Settings >>			
› Function Key		Apply		

• Line : choose one line (SIP1 or SIP2 or...).

• User Name : fill in the extension number (The user name provided in SIP account on IPPBX).

• **Display Name** : set the name you want to appear on other phone's display when calling other phones.

• Authentication Name : fill in the extension's (The user name provided in SIP account on IPPBX).

• **Authentication Password** : fill in the extension's "Registration Password" provided in SIP account on IPPBX.

- SIP Proxy Server Address : fill in your IPPBX IP address.
- SIP Proxy Server Port : default port is 5060.
 - 6. Active: Enabled
 - 7. Click "Apply".
 - Check the extensions status. If the extension is registered to your IPPBX successfully, the "Line Status" will show "Registered".

	SIP Dial Peer	Dial Plan	Basic Settings SIP Hotspot	
› System				
> Network	Line SIP 1 V Basic Settings >>			
> Line	Line Status	Registered	SIP Proxy Server Address	192.168.9.144
	Username	1000	SIP Proxy Server Port	5060
> Phone settings	Display name	1000	Outbound proxy add.	
	Authentication Name	1000	Outbound proxy port	
> Dhonabaak	Authentication Password		Realm	
Phonebook	Activate	e		
> Call logs	Codecs Settings >>			
> Function Key	Advanced Settings >>			
		Apply		